

Chamber Cleaning Kit

Chamber Cleaning Kit
for the ONCORE Pro Automated Slide Stainer
901-OPRI6031K-052623

Catalog Number: OPRI6031K C8

Description: 8 cleaning cycles

Intended Use:

For In Vitro Diagnostic Use

Chamber Cleaning Kit consists of three solutions intended for removing DAB residue and cleaning surfaces that have contacted DAB chromogen in the ONCORE Pro Automated Slide Stainer.

Summary & Explanation:

The Chamber Cleaning Kit includes reagents for cleaning the tubing and chamber surfaces that come in contact with 3,3'-diaminobenzidine (DAB) in the ONCORE Pro Automated Slide Stainer. During routine staining, DAB residue may be left behind on these surfaces. Regular use of the Chamber Cleaning Kit is recommended to remove DAB residue and prevent a hue on slides. Please refer to the ONCORE Pro Automated Slide Staining System User Manual for the recommended cleaning schedule.

Known Applications:

Cleaning of the ONCORE Pro Automated Slide Stainer.

Reagents Provided:

Chamber Cleaning Kit is comprised of 3 cleaning solutions in pre-filled vials, plus empty vials for users to fill with deionized (DI) water. One kit is sufficient to perform 8 cleaning cycles:

Clean 1 (OPRI6032 C8), 8 cleaning cycles, 1 vial x 13 mL
Clean 2 (OPRI6033 C8), 8 cleaning cycles, 1 vial x 13 mL
Clean 3 (OPRI6034 C2), 2 cleaning cycles, 5 vials x 14 mL
DI Water (OPRI6035 C1), 1 cleaning cycle, 16 vials

Reconstitution, Dilution and Mixing:

Each DI Water vial should be filled to the neck of the vial with DI water before placing on the instrument for use. No other preparation is required.

Storage and Stability:

Store at room temperature. The product is stable to the expiration date printed on the label, when stored under these conditions. Do not use after expiration date.

Instructions for Use:

Refer to the ONCORE Pro Automated Staining System User Manual for detailed instructions on instrument operation and the recommended cleaning schedule. To use the Chamber Cleaning Kit:

1. Press "Load/Unload Slides Slides, if chamber lids are in the down position."
2. Place a blank slide in each of the 36 slide modules.
3. Highlight all 36 slide positions.
4. Press "Assign Protocols."
5. Select "Clean Chamber."
6. Press "Scan Reagents."

7. Load one vial each of Clean 1 (OPRI6032C8), Clean 2 (OPRI6033C8), and Clean 3 (OPRI6034C2) into the reagent tray. Also load two vials of DI Water (filled with DI water) into the reagent tray.

8. Press "Scan Reagents."

Instructions for Use Cont'd:

9. Verify sufficient wash buffer is available and the waste container is empty.

10. Press "Start Staining Process."

Precautions:

1. Refer to reagent Safety Data Sheet for precautions.
2. Do not use reagent after the expiration date printed on the vial.



IRRITANT

Technical Support:

Contact Biocare's Technical Support at 1-800-542-2002 for questions regarding this product.